

Winding Number Transition at Finite Temperature : Mottola-Wipf model with and without Skyrme term

D. K. Park^a, Hungsoo Kim^b, Soo-Young Lee^a

^a *Department of Physics, Kyungnam University, Masan, 631-701, Korea.*

^b *Department of Physics, Korea Advanced Institute of Science and Technology,
Taejeon, 305-701, Korea.*

(February 1, 2008)

Abstract

The winding number transition in the Mottola-Wipf model with and without Skyrme term is examined. For the model with Skyrme term the number of discrete modes of the fluctuation operator around sphaleron is shown to be dependent on the value of λm^2 . Following Gorokhov and Blatter we derive a sufficient condition for the sharp first-order transition, which indicates that first-order transition occurs when $0 < \lambda m^2 < 0.0399$ and $2.148 < \lambda m^2$. In the intermediate region of λm^2 the winding number transition is conjectured to be smooth second order. For the model without Skyrme term the winding number transition is always first order regardless of the value of parameter.

I. INTRODUCTION

Quantum tunneling is one of the most fascinating phenomenon arised due to pure quantum effect and has profound physical implications in many fundamental phenomena in various branches of physics. After Langer [1] and Coleman [2] opened a door of the computational methodology for the investigation of the tunneling using a classical Euclidean solution called instanton or bounce, its generalization to the finite temperature tunneling or thermal activation is one of the long-standing subject in this field. It is well-known that as temperature increases from zero temperature the pure quantum tunneling at low temperature is gradually changed to the thermal activation at high temperature via thermally assisted tunneling region. This means there is a phase transition between sphaleron [3]-dominated high temperature regime and the instanton-dominated low temperature regime. This phase transition was explored within quantum mechanical models by Affleck [4] and cosmological models by Linde [5] about two decades ago. Both of them argued that there exist periodic solutions [6] which govern the tunneling at intermediate temperature regime and interpolate smoothly between vacuum instanton and sphaleron. Using a terminology of the statistical mechanics this phenomenon can be referred to second-order transition.

Chudnovsky [7], however, showed that this argument is not generic. Using a simple quantum mechanical model, he derived a relation

$$\frac{dS_E}{d\tau} = E > 0, \tag{1.1}$$

where S_E and τ are Euclidean classical action and period of periodic solution, respectively. Eq.(1.1) allows one to determine the temperature($T = 1/\tau$)-dependence of action(S_E) from energy(E)-dependence of period(τ). In fact, this is completely analogous to the plot of free enthalpy-vs-pressure of a van der Waals gas whose equation of state is determined as pressure-vs-volume. If, for example, E -dependence of τ is monotonic function, T -dependence of S_E becomes also monotonic, and eventually is merged to the action for the sphaleron solution smoothly. Since decay rate is proportional to e^{-S_E} , this case can be referred to

second-order transition. If, however, E -dependence of τ is not monotonic and has one minimum, T -dependence of S_E can be double-valued function in some region of domain of definition and it results in a sharp crossover from instanton-dominated low temperature regime to sphaleron-dominated high temperature regime. This is an example of first-order transition. Recently, his idea is realized at the spin tunneling system [8] in condensed matter physics.

Subsequently, Gorokhov and Blatter [9] extended Chudnovsky's idea and derived a sufficient condition for the first-order transition using only small fluctuation around sphaleron. Recently, their idea is extended [10] for the application to the model when mass is position-dependent. Although they derived the criterion to apply it to the some fields of the condensed matter physics [9,11], its application to the covariant field theories is straightforward. In fact, this criterion is applied to the four-dimensional scalar field theory with a asymmetric double well potential and the lower and upper bounds of the critical value of symmetry breaking parameter is calculated [12]. Recently, same criterion with that of Gorokhov and Blatter is derived again through completely different point of view by counting carefully the number of negative modes for the full hessian of periodic solution near sphaleron [13].

In this paper we will examine the winding number transition of the Mottola-Wipf(MW) model [14] with and without Skyrme term [15] and clarify the type of the transition in the full range of parameter space. Since the method of Ref. [13] for the study of winding number transition needs a periodic instanton solution which is very complicated [16] in this model, we will follow the procedure of Ref. [9].

MW model, non-linear $O(3)$ model with a soft symmetry breaking term, is usually adopted as a toy model for the study of the baryon number violation in electroweak theory [17]. Although localized vacuum instanton does not exist in this model, the analytical expression of the sphaleron solution was derived by paralleling Manton's original argument in Ref. [14]. The reason why MW model can be used as a toy model for a investigation of baryon-number violation in the electroweak theory is nicely explained in Ref. [14]. For a completeness we summarize it briefly. If one defines two component field

$$\psi = \begin{pmatrix} \psi_1 \\ \psi_2 \end{pmatrix} \quad (1.2)$$

such that $\phi^a = \psi^\dagger \sigma^a \psi$ where ϕ^a is scalar field of MW model and σ^a is usual Pauli matrix. Introducing gauge field $A_\mu = (\psi^\dagger \partial_\mu \psi - \partial_\mu \psi^\dagger \psi)/2i$, one can show that the winding number Q of MW model which is defined as

$$Q = \frac{1}{8\pi} \int d^2x \epsilon_{\mu\nu} \vec{\phi} \cdot (\partial_\mu \vec{\phi} \times \partial_\nu \vec{\phi}) \quad (1.3)$$

is reduced to

$$\frac{1}{4\pi} \int d^2x \epsilon_{\mu\nu} F_{\mu\nu}. \quad (1.4)$$

The integrand in Eq.(1.4) is nothing but an chiral anomaly [18] of massless fermion field coupled to $U(1)$ gauge field. Through index theorem the transition in MW model can be interpreted as tunneling which connects states with different chiral fermion numbers.

In order to make a modified model which supports a localized vacuum instanton as well as sphaleron, Piette *et al* [19] added a Skyrme term to this model. In this modified model whose action and constraint are

$$S = \frac{1}{g^2} \int d\tau dx \left[\frac{1}{2} \partial_\mu \phi^a \partial_\mu \phi^a + m^2 (1 + \phi^3) + \frac{\lambda}{8} \phi_{\mu\nu}^{ab} \phi_{\mu\nu}^{ab} \right] \quad (1.5)$$

$$\phi^a \phi^a = 1, \quad a = 1, 2, 3 \quad \mu, \nu = \tau, x$$

where $\phi_{\mu\nu}^{ab} = \partial_\mu \phi^a \partial_\nu \phi^b - \partial_\nu \phi^a \partial_\mu \phi^b$, sphaleron is identical to that of MW model whose action is Eq.(1.5) with $\lambda = 0$ and localized instanton can be obtained numerically. Winding number transition between instanton-dominated and sphaleron-dominated regimes in this model are discussed at particular value of parameter, $\lambda m^2 = 0.001$, in Ref. [20]. In this paper we will discuss the winding number transition in the full range of parameter space.

The paper is organized as follows. In Sec.II we will briefly review Gorokhov and Blatter's procedure in covariant scalar field theory. In Sec.III we will expand the field equation of Mottola-Wipf-Skyrme(MWS) model around sphaleron solution by introducing the fluctuation fields u and v . The spectra of the spatial fluctuation operators $\hat{h}_u$ and $\hat{h}_v$ are discussed

at Sec.IV. In Sec.V, following Gorokhov and Blatter, we will examine the winding number transition in MWS model. It will be shown that the type of transition is either first-order or second-order depending on the value of λm^2 . In Sec.VI the winding number transition in MW model will be discussed. It will be shown that the type of transition in this model is always first order regardless of value of parameter. In Sec.VII a brief conclusion will be given.

II. CRITERION FOR SHARP FIRST-ORDER TRANSITION

In this section we will review the procedure of Ref. [9] briefly in the covariant field theory. The Euclidean action we will consider is

$$S = \int dx \left[\frac{1}{2} \partial_\mu \phi \partial_\mu \phi + V(\phi) \right] \quad (2.1)$$

where field equation is

$$\square \phi = V'(\phi). \quad (2.2)$$

Although we do not need a specific form of $V(\phi)$, we assume field equation allows periodic instanton and sphaleron configurations. Since sphaleron ϕ_{sph} is static configuration, its equation of motion reads

$$\frac{\partial^2 \phi_{sph}}{\partial x^2} = V'(\phi_{sph}). \quad (2.3)$$

Now, we consider a small fluctuation $\eta(x, \tau)$ around sphaleron solution. If one uses Taylor expansion in potential, it is easy to show $\eta(x, \tau)$ satisfies upto the order of η^3

$$\hat{l}\eta(x, \tau) = \hat{h}\eta(x, \tau) + G_2[\eta] + G_3[\eta] \quad (2.4)$$

where $\hat{l} = \frac{\partial^2}{\partial \tau^2}$, $\hat{h} = -\frac{\partial^2}{\partial x^2} + V''(\phi_{sph})$, $G_2[\eta] = \frac{1}{2}V'''(\phi_{sph})\eta^2$, and $G_3[\eta] = \frac{1}{6}V''''(\phi_{sph})\eta^3$. The main idea of Ref. [9] is to compare the frequency of $\eta(x, \tau)$ with that of sphaleron by solving Eq.(2.4) perturbatively, which yields a sufficient condition for the first-order transition.

Here, the frequency of sphaleron ω_{sph} means frequency of the periodic instanton solution when periodic instanton approaches to the sphaleron solution.

To the lowest order in perturbation we use *ansatz*

$$\eta(x, \tau) = au_0(x) \cos \omega_{sph} \tau. \quad (2.5)$$

Here, a is a small parameter, which is associated with small amplitude of periodic solution whose center is ϕ_{sph} at quantum mechanical model. Substituting Eq.(2.5) into Eq.(2.4) while neglecting terms of order higher than a one obtains

$$\hat{h}u_0(x) = l(\omega_{sph})u_0(x) \quad (2.6)$$

where $l(\omega) \equiv -\omega^2$. Since spatial operator $\hat{h}$ has only one negative mode and $l(\omega_{sph}) < 0$, $u_0(x)$ and $l(\omega_{sph})$ are nothing but the ground state eigenfunction and eigenvalue of $\hat{h}$, respectively. This fact allows one to calculate ω_{sph} by solving the spectrum of $\hat{h}$.

To next order perturbation we use

$$\eta(x, \tau) = au_0(x) \cos \omega \tau + a^2 \eta_1(x, \tau) \quad (2.7)$$

where ω is the correction to the frequency ω_{sph} . Inserting Eq.(2.7) into Eq.(2.4) it is easy to obtain

$$\eta_1 = (\hat{l} - \hat{h})^{-1} \chi_1 \quad (2.8)$$

where

$$\chi_1 = \frac{1}{a} [l(\omega_{sph}) - l(\omega)] u_0(x) \cos \omega \tau + G_2[u_0] \cos^2 \omega \tau. \quad (2.9)$$

Since $\hat{l} - \hat{h}$ has zero mode $| u_0(x) \cos \omega \tau \rangle$, we can escape infinity in Eq.(2.8) if and only if a condition $\langle u_0(x) \cos \omega \tau | \chi_1 \rangle = 0$ holds. This condition requires no shift in the frequency $\omega = \omega_{sph}$, which means that next order perturbation must be performed to find frequency shift. Before we go to the next order, it is in order to compute η_1 explicitly. It is straightforwardly achieved from Eq.(2.8):

$$\eta_1(x, \tau) = g_1(x) + g_2(x) \cos 2\omega_{sph}\tau \quad (2.10)$$

where

$$\begin{aligned} g_1(x) &= -\frac{1}{2}\hat{h}^{-1}G_2[u_0] \\ g_2(x) &= -\frac{1}{2}[\hat{h} - l(2\omega_{sph})]^{-1}G_2[u_0]. \end{aligned} \quad (2.11)$$

Next order perturbation can be done by using

$$\eta(x, \tau) = au_0(x) \cos \omega\tau + a^2\eta_1(x, \tau) + a^3\eta_2(x, \tau). \quad (2.12)$$

Substituting Eq.(2.12) into Eq.(2.4) and neglecting terms of order a^4 and higher, one gets

$$\eta_2(x, \tau) = a^{-3}(\hat{l} - \hat{h})^{-1} [\chi_2^{(0)} + \chi_2^{(1)} \cos \omega\tau + \chi_2^{(2)} \cos 2\omega\tau + \chi_2^{(3)} \cos 3\omega\tau] \quad (2.13)$$

where

$$\begin{aligned} \chi_2^{(0)} &= a^2 \left[\hat{h}g_1(x) + \frac{1}{2}G_2[u_0] \right] \\ \chi_2^{(1)} &= -a [l(\omega) - l(\omega_{sph})] u_0(x) \\ &\quad + a^3 \left[\frac{\partial G_2[\xi]}{\partial \xi} \Big|_{\xi=u_0} \left(g_1(x) + \frac{1}{2}g_2(x) \right) + \frac{3}{4}G_3[u_0] \right] \\ \chi_2^{(2)} &= a^2 \left[[\hat{h} - l(2\omega)]g_2(x) + \frac{1}{2}G_2[u_0] \right] \\ \chi_2^{(3)} &= a^3 \left[\frac{1}{2} \frac{\partial G_2[\xi]}{\partial \xi} \Big|_{\xi=u_0} g_2(x) + \frac{1}{4}G_3[u_0] \right]. \end{aligned} \quad (2.14)$$

The infinity problem mentioned above yields another condition $\langle u_0(x) | \chi_2^{(1)} \rangle = 0$, which results in

$$l(\omega) - l(\omega_{sph}) = -\frac{a^2}{2 \langle u_0 | u_0 \rangle} \langle u_0 | f[u_0] \rangle \quad (2.15)$$

where

$$f[u_0] = \frac{\partial G_2[\xi]}{\partial \xi} \Big|_{\xi=u_0} \left[\hat{h}^{-1} + \frac{1}{2}[\hat{h} - l(2\omega_{sph})]^{-1} \right] G_2[u_0] - \frac{3}{2}G_3[u_0]. \quad (2.16)$$

If the spectrum of $\hat{h}$, $\hat{h} | u_n \rangle = h_n | u_n \rangle$, is completely solved, $\langle u_0 | f[u_0] \rangle$ is reduced to

$$\langle u_0 | f[u_0] \rangle = 2 \sum_n \left(\frac{1}{h_n} + \frac{1}{2 h_n - l(2\omega_{sph})} \right) |\langle G_2[u_0] | u_n \rangle|^2 - \frac{3}{2} \langle u_0 | G_3[u_0] \rangle. \quad (2.17)$$

One may worry for the use of Eq.(2.17) due to zero mode of $\hat{h}$, say $h_1 = 0$. It is, however, easy to show that it does not cause any problem if one realizes $\langle G_2[u_0] | u_1 \rangle = 0$ because of odd parity of u_1 .

Before we derive a sufficient condition for the sharp transition, it may be helpful to comment on the two kinds of field theoretical tunneling models. One kind(case I) consists of models which support localized vacuum instanton and sphaleron. The usual quantum mechanical model and MWS model plunge into this case. In these models the first-order phase transition takes place as usual quantum mechanical cases. The typical figure of first-order transition in case I is given in Fig.1(a). Another kind(case II) consists of models which does not support localized vacuum instanton. The MW model and electroweak theory are categorized in this case. In these models the low energy periodic instanton is built out of constraint instanton [6] whose period goes to zero at $E \rightarrow 0$. Applying a relation (1.1) one can get a typical figure of first-order transition in case II which is shown in Fig.1(b). In both cases the first-order transition occurs when $\omega > \omega_{sph}$, which results in

$$\langle u_0 | f[u_0] \rangle > 0. \quad (2.18)$$

We will use this criterion to determine the types of transition in the full range of parameter space in MWS and MW models.

III. FLUCTUATION AROUND SPHALERON IN MWS MODEL

The field equation of MWS model whose action is given at Eq.(1.5) is easily derived by introducing and subsequently removing a Lagrange multiplier:

$$(\delta^{ab} - \phi^a \phi^b) \left[\square \phi^b + \lambda \partial_\mu (\phi_{\mu\nu}^{bc} \partial_\nu \phi^c) \right] = m^2 (\delta^{a3} - \phi^a \phi^3). \quad (3.1)$$

Since Skyrme term does not contribute to field equation for static sphaleron [19], sphaleron is same with that of MW model which is derived at Ref. [14]:

$$\phi_{sph} = (\sin \xi_{sph}, 0, -\cos \xi_{sph}) \quad (3.2)$$

where

$$\xi_{sph} = 2 \sin^{-1}(\text{sech} mx). \quad (3.3)$$

Now, we introduce small fluctuation fields u and v around sphaleron such as

$$\phi = \frac{1}{\sqrt{1+u^2}} (\sin(\xi_{sph} + v), u, -\cos(\xi_{sph} + v)). \quad (3.4)$$

The expansion of the field equation (3.1) in terms of u and v is very tedious, but straightforward:

$$\hat{l} \begin{pmatrix} u \\ v \end{pmatrix} = \hat{h} \begin{pmatrix} u \\ v \end{pmatrix} + \begin{pmatrix} G_2^u(u, v) \\ G_2^v(u, v) \end{pmatrix} + \begin{pmatrix} G_3^u(u, v) \\ G_3^v(u, v) \end{pmatrix} + \dots \quad (3.5)$$

where

$$\begin{aligned} \hat{l} &= \begin{pmatrix} \frac{\partial^2}{\partial \tau^2} & 0 \\ 0 & \frac{\partial^2}{\partial \tau^2} \end{pmatrix} & \hat{h} &= \begin{pmatrix} \hat{h}_u & 0 \\ 0 & \hat{h}_v \end{pmatrix} \end{aligned} \quad (3.6)$$

$$\begin{aligned} G_2^u(u, v) &= \frac{\text{sech} mx}{1 + 4\lambda m^2 \text{sech}^2 mx} \left[2m^2 \tanh mx (uv - \lambda \dot{u}\dot{v}) - 4muv' + 2\lambda m(2\dot{u}'\dot{v} - 2\ddot{u}v' + u'\ddot{v} - \dot{u}\dot{v}') \right] \\ G_2^v(u, v) &= \text{sech} mx \left[-m^2 \tanh mx (u^2 - v^2 - 2\lambda \dot{u}^2) + 4muu' + 2\lambda m(\ddot{u}u' - \dot{u}\dot{u}') \right] \\ G_3^u(u, v) &= \frac{1}{1 + 4\lambda m^2 \text{sech}^2 mx} \left[2u(\dot{u}^2 + u'^2) - u(\dot{v}^2 + v'^2) - \frac{m^2}{2}(1 - 2\text{sech}^2 mx)(uv^2 - u^3) \right. \\ &\quad \left. + \lambda \left[-\ddot{u}v'^2 - \dot{u}v'\dot{v}' + 2\dot{u}'\dot{v}v' + u'\ddot{v}v' - u'\dot{v}\dot{v}' \right. \right. \\ &\quad \left. \left. + \dot{u}\dot{v}v'' - u''\dot{v}^2 + 4m^2 \text{sech}^2 mx(3u\dot{u}^2 + u^2\ddot{u}) \right] \right] \\ G_3^v(u, v) &= 2u(\dot{u}\dot{v} + u'v') + \frac{m^2}{6}(1 - 2\text{sech}^2 mx)(3u^2v - v^3) \\ &\quad + \lambda \left[-\dot{u}\dot{u}'v' - \dot{u}^2v'' - u'^2\ddot{v} - \dot{u}'u'\dot{v} + 2\dot{u}u'\dot{v}' + \dot{u}u''\dot{v} + \ddot{u}u'v' \right]. \end{aligned}$$

Here, prime and dot mean differentiation with respect to x and τ respectively, and $\hat{h}_u$ and $\hat{h}_v$ are

$$\begin{aligned}\hat{h}_u &= \frac{1}{1 + 4\lambda m^2 \text{sech}^2 mx} \left[-\frac{\partial^2}{\partial x^2} + m^2(1 - 6\text{sech}^2 mx) \right] \\ \hat{h}_v &= -\frac{\partial^2}{\partial x^2} + m^2(1 - 2\text{sech}^2 mx).\end{aligned}\tag{3.7}$$

It is interesting that Skyrme term contributes only modification of $\hat{h}_u$, not $\hat{h}_v$. Apart from denominator in $\hat{h}_u$ the eigenvalue equations of $\hat{h}_u$ and $\hat{h}_v$ are usual Pöschl-Teller type which can be solved completely [21]. The denominator in $\hat{h}_u$ modifies the spectrum which will be discussed in next section.

IV. SPECTRA OF $\hat{h}_u$ AND $\hat{h}_v$

Consider an eigenvalue equation of the usual Pöschl-Teller type potential:

$$\left[-\frac{d^2}{dx^2} + V(x) \right] \psi_n(x) = \lambda_n \psi_n(x) \tag{4.1}$$

where

$$V(x) = \omega^2 - \frac{V_0}{\cosh^2 \omega x}. \tag{4.2}$$

It is well-known that Eq.(4.1) has both finite discrete modes, whose number is dependent on

$$s = \frac{1}{2} \left[-1 + \sqrt{1 + \frac{4V_0}{\omega^2}} \right], \tag{4.3}$$

and continuum states. The spectrum and eigenfunctions are summarized as follows [21];

(1) Discrete modes

$$\begin{aligned}\lambda_n &= \omega^2 [1 - (s - n)^2] \quad (n = 0, 1, \dots, n_{max} < s) \\ \psi_n(x) &= \sqrt{\frac{\omega}{n!}} \sqrt{\frac{\Gamma(1 + 2s - n)}{\Gamma(1 + s - n)\Gamma(s - n)}} 2^{n-s} \cosh^{n-s} \omega x \\ &\quad \times {}_2F_1(-n, 1 + 2s - n; s - n + 1; \frac{1}{2}(1 - \tanh \omega x))\end{aligned}\tag{4.4}$$

(2) Continuum modes

$$\lambda_k = \omega^2 + k^2 \quad (4.5)$$

$$\psi_k(x) = \frac{1}{\sqrt{2\pi}} \frac{\Gamma(-s - \frac{ik}{\omega})\Gamma(1 + s - \frac{ik}{\omega})}{\Gamma(-\frac{ik}{\omega})\Gamma(1 - \frac{ik}{\omega})} e^{ikx}$$

$$\times {}_2F_1(s+1, -s; 1 - \frac{ik}{\omega}; \frac{1}{2}(1 - \tanh \omega x)).$$

Here, $\Gamma(a)$ and ${}_2F_1(a, b; c; z)$ are usual gamma and hypergeometric functions. Since eigenvalue equation for $\hat{h}_v$, $\hat{h}_v \varphi_n(x) = \epsilon_n^v \varphi_n(x)$, is exactly Pöschl-Teller type equation, it is very easy to find its spectrum and eigenfunctions, which is summarized at Table I.

Now, let us consider eigenvalue equation of $\hat{h}_u$;

$$\hat{h}_u \psi_n(x) = \epsilon_n^u \psi_n(x). \quad (4.6)$$

After rearranging Eq.(4.6) one can show that it is possible to make it as usual Pöschl-Teller type provided the following explicit ϵ_n^u -dependence of s is allowed ;

$$s = \frac{1}{2} \left[\sqrt{25 + 16\lambda\epsilon_n^u} - 1 \right]. \quad (4.7)$$

After eliminating ϵ_n^u by using Eq.(4.4) and (4.7) one can arrive at conclusion that different s -value is assigned to each discrete mode,

$$s_n = \frac{(8n\lambda m^2 - 1) + \sqrt{64\lambda^2 m^4 - 16(n^2 + n - 7)\lambda m^2 + 25}}{2(1 + 4\lambda m^2)}. \quad (4.8)$$

Now, we can solve Eq.(4.8) for non-negative integer n under requirements $s > 0$ and $s > n$, which results in a fact that the number of discrete modes is dependent on λm^2 . For example, there are three discrete modes($n = 0, 1, 2$) for $0 < \lambda m^2 \leq 3/2$. And, one more discrete mode appears for $3/2 < \lambda m^2 \leq 7/2$. Generally, there are n discrete modes for $\frac{(n-1)^2 + (n-1) - 6}{4} < \lambda m^2 \leq \frac{n^2 + n - 6}{4}$. Parameter-dependence of discrete spectrum is explicitly shown at Fig.2. It is worthwhile noting that $n = 0$ is negative mode and $n = 1$ is zero mode which indicates that u is fluctuation field around unstable configuration.

The continuum spectrum of $\hat{h}_u$ is more simple. If one follows the same procedure, it is easy to show that continuum spectrum and correspondent eigenfunctions are exactly same with those of Eq.(4.5) provided s is replaced by

$$s_k = \frac{-1 + \sqrt{25 + 16\lambda(m^2 + k^2)}}{2}. \quad (4.9)$$

Table II shows a complete spectrum of $\hat{h}_u$ for $0 < \lambda m^2 < 3/2$.

V. CRITERION FOR FIRST-ORDER TRANSITION IN MWS MODEL

In this section we will derive the criterion for the first-order transition in MWS model by following Gorokhov and Blatter. To do the lowest order perturbation we choose a *ansatz*

$$\begin{pmatrix} u \\ v \end{pmatrix} = a \begin{pmatrix} u_0(x) \\ v_0(x) \end{pmatrix} \cos \Omega_{sph} \tau \quad (5.1)$$

where a is discussed at the below of Eq.(2.5). Inserting Eq.(5.1) into Eq.(3.5) and neglecting terms of order higher than a we obtain

$$\hat{h} \begin{pmatrix} u_0(x) \\ v_0(x) \end{pmatrix} = l(\Omega_{sph}) \begin{pmatrix} u_0(x) \\ v_0(x) \end{pmatrix} \quad (5.2)$$

where $l(\Omega) \equiv -\Omega^2$. Based on the analysis of Sec. IV, it is easy to show that $\hat{h}$ has only one negative mode whose eigenvalue and eigenfunction are $\epsilon_0^u = -m^2(s_0^2 - 1)$ and $\begin{pmatrix} \psi_0(x) \\ 0 \end{pmatrix}$, respectively. Here, s_0 is obtained from Eq.(4.8) by letting $n = 0$;

$$s_0 = \frac{\sqrt{1 + 4(1 + 4\lambda m^2)(6 + 4\lambda m^2)} - 1}{2(1 + 4\lambda m^2)}. \quad (5.3)$$

Hence, the lowest perturbation shows

$$\begin{aligned} \Omega_{sph} &= \sqrt{s_0^2 - 1}m \\ u_0(x) &= \psi_0(x) = 2^{-s_0} \sqrt{\frac{m\Gamma(1 + 2s_0)}{\Gamma(s_0)\Gamma(1 + s_0)}} \cosh^{-s_0} mx \\ v_0(x) &= 0. \end{aligned} \quad (5.4)$$

Now, let us start the next order perturbation by substituting

$$\begin{pmatrix} u(x, \tau) \\ v(x, \tau) \end{pmatrix} = \begin{pmatrix} au_0(x) \cos \Omega \tau + a^2 u_1(x, \tau) \\ a^2 v_1(x, \tau) \end{pmatrix} \quad (5.5)$$

into Eq.(3.5). As commented in Sec.II, Ω is the correction to the frequency Ω_{sph} . Neglecting higher order terms one arrives at the following equation:

$$\begin{pmatrix} u_1(x, \tau) \\ v_1(x, \tau) \end{pmatrix} = (\hat{l} - \hat{h})^{-1} \vec{\chi}_1 \quad (5.6)$$

where

$$\vec{\chi}_1 = \frac{1}{a} [l(\Omega_{sph}) - l(\Omega)] \begin{pmatrix} u_0(x) \cos \Omega \tau \\ 0 \end{pmatrix} + \begin{pmatrix} 0 \\ H_1(x, \tau) \end{pmatrix}. \quad (5.7)$$

Here, $H_1(x, \tau)$ is

$$H_1(x, \tau) = 2^{-2s_0} \frac{m^3 \Gamma(1 + 2s_0)}{\Gamma(s_0) \Gamma(1 + s_0)} \frac{\sinh mx}{\cosh^{2s_0+2} mx} \times \left[-(4s_0 + 1) \cos^2 \Omega \tau + 2\lambda \Omega^2 (\sin^2 \Omega \tau + s_0) \right]. \quad (5.8)$$

Using same argument given at Sec.II, we need a condition

$$\left\langle \begin{pmatrix} u_0 \cos \Omega \tau \\ 0 \end{pmatrix} \right| \vec{\chi}_1 \rangle = 0 \quad (5.9)$$

to escape an infinity arised due to inversion of $\hat{l} - \hat{h}$. The condition (5.9) is automatically satisfied if $\Omega = \Omega_{sph}$, which means there is no frequency shift in the present order of perturbation.

Before we go to next order, let us compute $u_1(x, \tau)$ and $v_1(x, \tau)$ explicitly. This is achieved by direct calculation, which needs a tedious, but straightforward procedure:

$$u_1(x, \tau) = 0 \quad (5.10)$$

$$v_1(x, \tau) = g_{v,1}(x) + g_{v,2}(x) \cos 2\Omega_{sph} \tau$$

where

$$\begin{aligned} g_{v,1}(x) &= 2^{-2s_0} \frac{m^3 \Gamma(1 + 2s_0)}{\Gamma(s_0) \Gamma(1 + s_0)} \left[2s_0(1 - \lambda \Omega_{sph}^2) + \left(\frac{1}{2} - \lambda \Omega_{sph}^2 \right) \right] \\ &\quad \times \hat{h}_v^{-1} \frac{\sinh mx}{\cosh^{2s_0+2} mx} \\ g_{v,2}(x) &= -2^{-2s_0} \frac{m^3 \Gamma(1 + 2s_0)}{\Gamma(s_0) \Gamma(1 + s_0)} \left(2s_0 + \frac{1}{2} + \lambda \Omega_{sph}^2 \right) \\ &\quad \times \left[l(2\Omega_{sph}) - \hat{h}_v \right]^{-1} \frac{\sinh mx}{\cosh^{2s_0+2} mx}. \end{aligned} \quad (5.11)$$

Now, let us perform next order perturbation with

$$\begin{pmatrix} u(x, \tau) \\ v(x, \tau) \end{pmatrix} = \begin{pmatrix} au_0(x) \cos \Omega \tau + a^3 u_2(x, \tau) \\ a^2 v_1(x, \tau) + a^3 v_2(x, \tau) \end{pmatrix}. \quad (5.12)$$

After inserting Eq.(5.12) into Eq.(3.5) we obtain

$$\begin{pmatrix} u_2(x, \tau) \\ v_2(x, \tau) \end{pmatrix} = (\hat{l} - \hat{h})^{-1} \vec{\chi}_2. \quad (5.13)$$

Here, we do not need full explicit form of $\vec{\chi}_2$ for the derivation of criterion for sharp winding number transition. The only one we need is the upper element in Eq.(5.13), which is

$$u_2(x, \tau) = (\hat{l} - \hat{h}_u)^{-1} \chi_2^u \quad (5.14)$$

where

$$\begin{aligned} \chi_2^u = & -\frac{1}{a^2} [l(\Omega) - l(\Omega_{sph})] u_0(x) \cos \Omega \tau \\ & + \frac{1}{1 + 4\lambda m^2 \text{sech}^2 mx} [G_{u,1}(x) \cos \Omega \tau + G_{u,2}(x) \cos 3\Omega \tau]. \end{aligned} \quad (5.15)$$

In Eq.(5.15) the explicit form of $G_{u,2}(x)$ is not needed also for the derivation of criterion.

The only one we need is $G_{u,1}(x)$ which is

$$\begin{aligned} G_{u,1}(x) = & 2^{-s_0} \left(\frac{m\Gamma(1+2s_0)}{\Gamma(s_0)\Gamma(1+s_0)} \right)^{\frac{1}{2}} \left[\frac{2m^2 \sinh mx}{\cosh^{s_0+2} mx} \left(g_{v,1} + \frac{1}{2} g_{v,2} - \lambda \Omega_{sph}^2 g_{v,2} \right) \right. \\ & \left. - \frac{4m}{\cosh^{s_0+1} mx} \left(g'_{v,1} + \frac{1}{2} g'_{v,2} - \lambda \Omega_{sph}^2 g'_{v,1} \right) \right] \\ & + 2^{-3s_0} \left(\frac{m\Gamma(1+2s_0)}{\Gamma(s_0)\Gamma(1+s_0)} \right)^{\frac{3}{2}} \left[\left[\frac{1}{2} \Omega_{sph}^2 + \frac{3}{8} m^2 (1 + 4s_0^2) \right] \cosh^{-3s_0} mx \right. \\ & \left. - \frac{3}{4} m^2 (1 + 2s_0^2) \cosh^{-3s_0-2} mx \right]. \end{aligned} \quad (5.16)$$

Hence, the condition $\langle u_0(x) \cos \Omega \tau \mid \chi_2^u \rangle = 0$ gives the correction to the frequency:

$$l(\Omega) - l(\Omega_{sph}) = a^2 \langle u_0(x) \mid \frac{\cosh^2 mx}{\cosh^2 mx + 4\lambda m^2} G_{u,1}(x) \rangle. \quad (5.17)$$

In order to change Eq.(5.17) to a more convenient form, we have to compute $g_{v,1}(x)$ and $g_{v,2}(x)$ explicitly which is performed in Appendix, where the following integral representations are obtained:

$$\begin{aligned}
g_{v,1}(x) &= \frac{(2s_0 + \frac{1}{2}) - \lambda m^2(s_0^2 - 1)(2s_0 + 1)}{4\pi(1 + s_0)\Gamma(s_0)\Gamma(1 + s_0)} \left[\int dk \frac{\Gamma\left(s_0 + \frac{1}{2} + \frac{ik}{2m}\right) \Gamma\left(s_0 + \frac{1}{2} - \frac{ik}{2m}\right)}{1 + k^2/m^2} \frac{k}{m} \sin kx \right. \\
&\quad \left. + \tanh mx \int dk \frac{\Gamma\left(s_0 + \frac{1}{2} + \frac{ik}{2m}\right) \Gamma\left(s_0 + \frac{1}{2} - \frac{ik}{2m}\right)}{1 + k^2/m^2} \cos kx \right] \\
g_{v,2}(x) &= \frac{(2s_0 + \frac{1}{2}) + \lambda m^2(s_0^2 - 1)}{4\pi(1 + s_0)\Gamma(s_0)\Gamma(1 + s_0)} \left[\int dk \frac{\Gamma\left(s_0 + \frac{1}{2} + \frac{ik}{2m}\right) \Gamma\left(s_0 + \frac{1}{2} - \frac{ik}{2m}\right)}{(4s_0^2 - 3) + k^2/m^2} \frac{k}{m} \sin kx \right. \\
&\quad \left. + \tanh mx \int dk \frac{\Gamma\left(s_0 + \frac{1}{2} + \frac{ik}{2m}\right) \Gamma\left(s_0 + \frac{1}{2} - \frac{ik}{2m}\right)}{(4s_0^2 - 3) + k^2/m^2} \cos kx \right].
\end{aligned} \tag{5.18}$$

By inserting Eq.(5.18) into Eq.(5.16) one can obtain double-integral representation of $G_{u,1}(x)$. Then, through some appropriate change of variables we get the final form of $l(\Omega) - l(\Omega_{sph})$:

$$\begin{aligned}
l(\Omega) - l(\Omega_{sph}) &= a^2 s^{-2s_0} \frac{m^3 \Gamma(1 + 2s_0)}{\Gamma^2(s_0) \Gamma^2(1 + s_0)} \\
&\times \left[\frac{(2s_0 + \frac{1}{2}) - \lambda m^2(s_0^2 - 1)(2s_0 + 1)}{2\pi(1 + s_0)} \int dy \frac{\sinh y}{\cosh^{2s_0} y (\cosh^2 y + 4\lambda m^2)^2} \right. \\
&\quad \times K_1(y) [J_1(y) + \tanh y J_2(y)] \\
&\quad + \frac{(2s_0 + \frac{1}{2}) + \lambda m^2(s_0^2 - 1)}{2\pi(1 + s_0)} \int dy \frac{\sinh y}{\cosh^{2s_0} y (\cosh^2 y + 4\lambda m^2)^2} \\
&\quad \times K_2(y) [J_3(y) + \tanh y J_4(y)] \\
&\quad \left. + 2^{-2s_0} \Gamma(1 + 2s_0) \left[\frac{16s_0^2 - 1}{8} \int \frac{dy}{\cosh^{4s_0-2} y (\cosh^2 y + 4\lambda m^2)} \right. \right. \\
&\quad \left. \left. - \frac{3(1 + 2s_0^2)}{4} \int \frac{dy}{\cosh^{4s_0} y (\cosh^2 y + 4\lambda m^2)} \right] \right]
\end{aligned} \tag{5.19}$$

where

$$\begin{aligned}
J_1(y) &= \int_{-\infty}^{\infty} dq \frac{q \left| \Gamma\left(s_0 + \frac{1+iq}{2}\right) \right|^2}{1 + q^2} \sin qy \\
J_2(y) &= \int_{-\infty}^{\infty} dq \frac{\left| \Gamma\left(s_0 + \frac{1+iq}{2}\right) \right|^2}{1 + q^2} \cos qy \\
J_3(y) &= \int_{-\infty}^{\infty} dq \frac{q \left| \Gamma\left(s_0 + \frac{1+iq}{2}\right) \right|^2}{q^2 + (4s_0^2 - 3)} \sin qy
\end{aligned} \tag{5.20}$$

$$\begin{aligned}
J_4(y) &= \int_{-\infty}^{\infty} dq \frac{|\Gamma(s_0 + \frac{1+iq}{2})|^2}{q^2 + (4s_0^2 - 3)} \cos qy \\
K_1(y) &= [-4s_0 - 1 + 2(1 + 2s_0)(s_0^2 - 1)\lambda m^2] \cosh^2 y + [-4s_0 + 3 + 2(2s_0 - 1)(s_0^2 - 1)\lambda m^2] 4\lambda m^2 \\
K_2(y) &= [-2s_0 - \frac{1}{2} - (s_0^2 - 1)\lambda m^2] \cosh^2 y + [-2s_0 + \frac{3}{2} - (s_0^2 - 1)\lambda m^2] 4\lambda m^2.
\end{aligned}$$

Fig. 3 shows the result of numerical calculation of $l(\Omega) - l(\Omega_{sph})$ with respect to λm^2 . From Fig. 3 we can conclude that MWS model exhibits sharp first order winding number transition when $0 < \lambda m^2 < 0.0399$ and $2.148 < \lambda m^2$. Ref. [20] shows first order transition when $\lambda m^2 = 0.001$, which is in agreement with our conclusion. Although Gorokhov and Blatter's method cannot determine the type of transition for $0.0399 < \lambda m^2 < 2.148$, it is easily conjectured using $2S_0/S_{sph}$ which is shown in Fig. 4. Here, S_0 is classical action of vacuum instanton and $S_{sph} = (2\pi/\Omega_{sph})E_{sph}$, where E_{sph} is space integration of classical Lagrangian for the static sphaleron solution, and interpreted as barrier height in usual Minkowski space. Fig. 4 indicates that $2S_0/S_{sph} < 1$ when $0 < \lambda m^2 < 0.006$ and $2.52 < \lambda m^2$, and $2S_0/S_{sph} > 1$ when $0.006 < \lambda m^2 < 2.52$. Hence, MWS model exhibits strong first-order transition when $0 < \lambda m^2 < 0.006$ and $2.52 < \lambda m^2$, and weak first-order transition when $0.006 < \lambda m^2 < 0.0399$ and $2.148 < \lambda m^2 < 2.52$ as shown in Fig. 5. From this fact we can conjecture that smooth second order transition occurs at intermediate region of λm^2 .

VI. WINDING NUMBER TRANSITION IN MW MODEL

In this section we will discuss the winding number transition in MW model by taking $\lambda \rightarrow 0$ limit in Eq.(5.19). Using integral formula [22]

$$\begin{aligned}
\int_0^{\infty} dx \frac{\sin ax}{\cosh \beta x} x^{2m+1} &= (-1)^{m+1} \frac{\pi}{2\beta} \frac{\partial^{2m+1}}{\partial a^{2m+1}} \frac{1}{\cosh \frac{a\pi}{2\beta}} \\
\int_0^{\infty} dx \frac{\cos ax}{\cosh \beta x} x^{2m} &= (-1)^m \frac{\pi}{2\beta} \frac{\partial^{2m}}{\partial a^{2m}} \frac{1}{\cosh \frac{a\pi}{2\beta}},
\end{aligned} \tag{6.1}$$

we can show straightforwardly

$$J_1(y) = \frac{\pi}{4} \frac{\sinh y (3 + 4 \cosh^2 y)}{\cosh^4 y} \tag{6.2}$$

$$\begin{aligned}
J_2(y) &= \frac{\pi}{4} \frac{1 + 4 \cosh^2 y}{\cosh^3 y} \\
J_3(y) &= \frac{\pi}{8} \int_0^\infty dq \frac{q(q^2 + 1)(q^2 + 9)}{(q^2 + 13) \cosh \frac{\pi q}{2}} \sin qy \\
J_4(y) &= \frac{\pi}{8} \int_0^\infty dq \frac{(q^2 + 1)(q^2 + 9)}{(q^2 + 13) \cosh \frac{\pi q}{2}} \cos qy \\
K_1(y) &= 2K_2(y) = -9 \cosh^2 y.
\end{aligned}$$

Hence, we can obtain $l(\Omega) - l(\Omega_{sph})$ by inserting Eq.(6.2) into Eq.(5.19). Since y -integration in this case is analytically solved if one uses integral formula [22],

$$\int_0^\infty dx \frac{\cos ax}{\cosh^{2n+1} \beta x} = \frac{\pi(a^2 + \beta^2)(a^2 + 3^2 \beta^2) \cdots [a^2 + (2n-1)^2 \beta^2]}{2(2n)! \beta^{2n+1} \cosh \frac{a\pi}{2\beta}}, \quad (6.3)$$

the final form of $l(\Omega) - l(\Omega_{sph})$ in MW model is simply

$$l(\Omega) - l(\Omega_{sph}) = -\frac{9a^2 m^3}{2} \left[\frac{1}{70} + \frac{\pi}{4096} I \right] \quad (6.4)$$

where

$$I = \int_0^\infty dq \frac{(q^2 + 1)^3 (q^2 + 9)^2}{(q^2 + 13) \cosh^2 \frac{\pi q}{2}}. \quad (6.5)$$

Numerical calculation shows $l(\Omega) - l(\Omega_{sph}) = -0.161116a^2 m^3$, which means sharp first-order transition in the full range of parameter space. This is in agreement with result of Ref. [16].

VII. CONCLUSION

In this paper we examine the winding number transition of the MW model with and without Skyrem term. For MWS model we expand the field equation around sphaleron solution, which yields the explicit form of the fluctuation operator. The spatial fluctuation operator is proven to be a kind of modified Pöschl-Teller type and its number of discrete modes is dependent on the value of λm^2 . The increment of λm^2 gives rise to the increase of the number of discrete modes, and eventually the infinite number of discrete modes arises as λm^2 approaches infinity.

Following Gorokhov and Blatter we derive the sufficient condition for the sharp first-order transition in this model, which indicates that first-order transition occurs when $0 < \lambda m^2 < 0.0399$ and $2.148 < \lambda m^2$. Computing $2S_0/S_{sph}$, we conjecture that the smooth second-order transition occurs in the intermediate region of λm^2 .

For MW model the criterion for the sharp transition can be easily derived by taking a $\lambda \rightarrow 0$ limit to that of MWS model. It is shown that the MW model always exhibits a first-order winding number transition regardless of the value of parameter.

MW model is frequently used as a toy model of sphaleron transition for the electroweak theory, and hence for the investigation of the baryon number violating processes. Recent study [23], however, on the sphaleron transition of $SU(2)$ -Higgs theory [24] has shown that smooth second-order sphaleron transition occurs when $6.665 < M_H/M_W < 12.03$ although first-order transition occurs when $M_H/M_W < 6.665$. Hence, MW model cannot play an important role as a toy model for the study of sphaleron transition of electroweak theory when Higgs are very massive than W particle. This means we need another toy model which exhibits a first-order and second-order sphaleron transition depending on the values of parameters involved in the model. Based on our study on the relation of number of negative modes and bifurcation point analyzed in Ref. [13], we have an opinion that this may be achieved by endowing a nontrivial topology to the space coordinate. This will be discussed elsewhere.

APPENDIX A: CALCULATION OF $g_{v,1}(x)$ AND $g_{v,2}(x)$

In this appendix we will calculate $g_{v,1}(x)$ and $g_{v,2}(x)$ defined at Eq.(5.11).

[1] $g_{v,1}(x)$

Using complete condition for $\hat{h}_v$, it is easy to show

$$\hat{h}_v^{-1} \frac{\sinh mx}{\cosh^{2s_0+2} mx} = \int \frac{dk}{k^2 + m^2} | \varphi_k > < \varphi_k | \frac{\sinh mx}{\cosh^{2s_0+2} mx} > \quad (\text{A1})$$

where $| \varphi_k >$ is defined at Table I. In Eq.(A1) $< \varphi_k | \frac{\sinh mx}{\cosh^{2s_0+2} mx} >$ can be calculated by making use of integral formula

$$\int_0^\infty dx \frac{\cos ax}{\cosh^\nu \beta x} = \frac{2^{\nu-2}}{\beta \Gamma(\nu)} \Gamma\left(\frac{\nu}{2} + \frac{ai}{2\beta}\right) \Gamma\left(\frac{\nu}{2} - \frac{ai}{2\beta}\right). \quad (\text{A2})$$

Inserting the result of $\langle \varphi_k | \frac{\sinh mx}{\cosh^{2s_0+2} mx} \rangle$ into Eq.(A1) one can obtain

$$\begin{aligned} g_{v,1}(x) &= \frac{(2s_0 + \frac{1}{2}) - \lambda m^2(s_0^2 - 1)(2s_0 + 1)}{4\pi(1 + s_0)\Gamma(s_0)\Gamma(1 + s_0)} \\ &\times \left[\int dk \frac{\Gamma\left(s_0 + \frac{1}{2} + \frac{ik}{2m}\right) \Gamma\left(s_0 + \frac{1}{2} - \frac{ik}{2m}\right)}{1 + k^2/m^2} \frac{k}{m} \sin kx \right. \\ &\quad \left. + \tanh mx \int dk \frac{\Gamma\left(s_0 + \frac{1}{2} + \frac{ik}{2m}\right) \Gamma\left(s_0 + \frac{1}{2} - \frac{ik}{2m}\right)}{1 + k^2/m^2} \cos kx \right]. \end{aligned} \quad (\text{A3})$$

$$[2] \ g_{v,2}(x)$$

Using complete condition for $\hat{h}_v$ again one can show directly

$$\begin{aligned} &[l(2\Omega_{sph}) - \hat{h}_v]^{-1} \frac{\sinh mx}{\cosh^{2s_0+2} mx} \\ &= -\frac{s^{2s_0}}{4\pi(1 + s_0)m^3\Gamma(1 + 2s_0)} \int dk \frac{\Gamma\left(s_0 + \frac{1}{2} + \frac{ik}{2m}\right) \Gamma\left(s_0 + \frac{1}{2} - \frac{ik}{2m}\right)}{(4s_0^2 - 3) + k^2/m^2} \left(\frac{k}{m} \sin kx + \tanh mx \cos kx \right). \end{aligned} \quad (\text{A4})$$

Inserting Eq.(A4) into Eq.(5.11) we obtain

$$\begin{aligned} g_{v,2}(x) &= \frac{(2s_0 + \frac{1}{2}) + \lambda m^2(s_0^2 - 1)}{4\pi(1 + s_0)\Gamma(s_0)\Gamma(1 + s_0)} \left[\int dk \frac{\Gamma\left(s_0 + \frac{1}{2} + \frac{ik}{2m}\right) \Gamma\left(s_0 + \frac{1}{2} - \frac{ik}{2m}\right)}{(4s_0^2 - 3) + k^2/m^2} \frac{k}{m} \sin kx \right. \\ &\quad \left. + \tanh mx \int dk \frac{\Gamma\left(s_0 + \frac{1}{2} + \frac{ik}{2m}\right) \Gamma\left(s_0 + \frac{1}{2} - \frac{ik}{2m}\right)}{(4s_0^2 - 3) + k^2/m^2} \cos kx \right]. \end{aligned} \quad (\text{A5})$$

In MW model($\lambda \rightarrow 0$, $s_0 \rightarrow 2$) $g_{v,1}(x)$ and $g_{v,2}(x)$ are simply expressed as follows:

$$\begin{aligned} g_{v,1}(x) &= \frac{3m}{16} \frac{\sinh mx}{\cosh^4 mx} (1 + 2 \cosh^2 mx) \\ g_{v,2}(x) &= \frac{3}{256m^2} \left[\frac{1}{m} \int dk \frac{k(k^2 + m^2)(k^2 + 9m^2)}{(k^2 + 13m^2) \cosh \frac{k\pi}{2m}} \sin kx + \tanh mx \int dk \frac{(k^2 + m^2)(k^2 + 9m^2)}{(k^2 + 13m^2) \cosh \frac{k\pi}{2m}} \cos kx \right]. \end{aligned} \quad (\text{A6})$$

REFERENCES

- [1] S. Langer, Ann. Phys. **54**, 258 (1969).
- [2] S. Coleman, Phys. Rev. **D15**, 2929 (1977).
- [3] In fact, sphaleron is an Euclidean classical solution of electroweak theory, which is associated with a trivial solution sitting at the barrier top. See
N. S. Manton, Phys. Rev. **D28**, 2019 (1983);
F. R. Klinkhamer and N. S. Manton, Phys. Rev. **D30**, 2212 (1984).
- [4] I. Affleck, Phys. Rev. Lett. **46**, 388 (1981).
- [5] A. Linde, Nucl. Phys. **B216**, 421 (1983).
- [6] S. Y. Khlebnikov, V. A. Rubakov, and P. Tinyakov, Nucl. Phys. **B367**, 334 (1991).
- [7] E. M. Chudnovsky, Phys. Rev. **A46**, 8011(1992).
- [8] J.-Q. Liang, H. J. W. Müller-Kirsten, D. K. Park, and F. Zimmerschied, Phys. Rev. Lett. **81**, 216 (1998).
- [9] D. A. Gorokhov and G. Blatter, Phys. Rev. **B56**, 3130 (1997).
- [10] H. J. W. Müller-Kirsten, D. K. Park, and J. M. S. Rana, to appear in Phys. Rev. B.
- [11] D. A. Gorokhov and G. Blatter, Phys. Rev. **B58**, 5486 (1998).
- [12] Hungsoo Kim, Soo-Young Lee, Sahng-Kyoon Yoo, D. K. Park, and Jae Kwan Kim, Phys. Lett. **B453**, 269 (1999).
- [13] Soo-Young Lee, Hungsoo Kim, D. K. Park, and Jae Kwan Kim, hep-th/9903070.
- [14] E. Mottola and A. Wipf, Phys. Rev. **D39**, 588 (1989).
- [15] T. H. R. Skyrme, Proc. Roy. Soc. Lon. **260**, 127 (1961).
- [16] S. Habib, E. Mottola, and P. Tinyakov, Phys. Rev. **D54**, 7774 (1996).

- [17] , L. G. Yaffe, Phys. Rev. **D40**, 3463 (1989).
- [18] R. Jackiw, in : Current Algebra and Anomalies, eds. S. B. Treiman, R. Jackiw, B. Zumino, and E. Witten (World Scientific, Singapore, 1985) see part of anomalous divergence and axial current.
- [19] B. M. A. G. Piette, H. J. W. Müller-Kirsten, D. H. Tchrakian, and W. J. Zakrzewski, Phys. Lett. **B320**, 294 (1994).
- [20] A. N. Kuznetsov and P. G. Tinyakov, Phys. Lett. **B406**, 76 (1997).
- [21] R. Jackiw, Rev. Mod. Phys. **49**, 681 (1977).
- [22] I. S. Gradshteyn and I. M. Ryzhik, *Table of Integrals, Series, and Product* (Academic Press, New York, 1965).
- [23] K. L. Frost and L. G. Yaffe, Phys. Rev. **D59**, 06513 (1999).
- [24] $SU(2)$ -Higgs theory is a bosonic sector of electroweak theory in the limit of vanishing weak mixing angle. See Ref. [17].

TABLES

	ϵ_n^v	$\varphi_n(x)$
$n = 0$	0	$\sqrt{\frac{m}{2}} \frac{1}{\cosh mx}$
$n = k$	$m^2 + k^2$	$\frac{1}{\sqrt{2\pi}} \frac{e^{ikx}}{1 + \frac{ik}{m}} \left(\frac{ik}{m} - \tanh mx \right)$

TABLE I. eigenvalues and eigenfunctions of $\hat{h}_v$

	ϵ_n^u	$\psi_n(x)$
$n = 0$	$m^2(1 - s_0^2)$	$\sqrt{\frac{m\Gamma(1+2s_0)}{\Gamma(s_0)\Gamma(1+s_0)}} \left(\frac{1}{2 \cosh mx} \right)^{s_0}$
$n = 1$	0	$\sqrt{\frac{3m}{2}} \frac{\sinh mx}{\cosh^2 mx}$
$n = 2$	$m^2[1 - (s_2 - 2)^2]$	$\sqrt{\frac{m\Gamma(2s_2-1)}{2\Gamma(s_2-1)\Gamma(s_2-2)}} \left(\frac{1}{2 \cosh mx} \right)^{s_2-2} \frac{(2s_2-1) \tanh^2 mx - 1}{2(s_2-1)}$
$n = k$	$m^2 + k^2$	$\frac{1}{\sqrt{2\pi}} \frac{\Gamma(-s_k - \frac{ik}{m})\Gamma(s_k + 1 - \frac{ik}{m})}{\Gamma(-\frac{ik}{m})\Gamma(1 - \frac{ik}{m})} e^{ikx} {}_2F_1 \left(s_k + 1, -s_k; 1 - \frac{ik}{m}; \frac{1}{2}(1 - \tanh mx) \right)$

TABLE II. eigenvalues and eigenfunctions of $\hat{h}_u$ when $0 < \lambda m^2 < \frac{3}{2}$

FIGURES

FIG. 1. Typical Action-vs-Period diagrams of first-order transition for (a) case I and (b) case II. Bold lines determine the winding number transitions.

FIG. 2. Discrete spectrum of $\hat{h}_u$. The number of discrete modes is dependent on the value of λm^2 . In fact, there are n discrete modes when $\frac{(n-1)^2+(n-1)-6}{4} < \lambda m^2 \leq \frac{n^2+n-6}{4}$.

FIG. 3. λm^2 -dependence of $l(\Omega) - l(\Omega_{sph})$. This figure shows that MWS model exhibits sharp first-order transition when $0 < \lambda m^2 < 0.0399$ and $2.148 < \lambda m^2$.

FIG. 4. λm^2 -dependence of $2S_0/S_{sph}$. Combining this figure and Fig.3 we can conclude that MWS model exhibits weak first-order transition when $0.006 < \lambda m^2 < 0.0399$ and $2.148 < \lambda m^2 < 2.52$. From this fact one can conjecture MWS model exhibits smooth second-order transition when $0.0399 < \lambda m^2 < 2.148$.

FIG. 5. (a) Action-vs-Period diagram of MWS model when $0 < \lambda m^2 < 0.006$ and $2.52 < \lambda m^2$. In this regime MWS model exhibits strong first-order sphaleron transition. (b) Action-vs-Period diagram of MWS model when $0.006 < \lambda m^2 < 0.0399$ and $2.148 < \lambda m^2 < 2.52$. In this regime MWS model exhibits weak first-order sphaleron transition. (c) Action-vs-Period diagram of MWS model when $0.0399 < \lambda m^2 < 2.148$, which is drawn by conjecture from the fact that MWS model exhibits weak first-order transition when $0.006 < \lambda m^2 < 0.0399$ and $2.148 < \lambda m^2 < 2.52$.




Fig.1 (a)




Fig.1 (b)




Fig.2




Fig.3




Fig.4




Fig.5 (a)




Fig.5 (b)




Fig.5 (c)